



320 Northpoint Parkway SE
 Suite B & C
 Acworth, GA 30102 USA
 Tel: 770-529-6800
 Fax: 770-529-6840
www.dmswireless.com

February 2009

| | |
|----------------------------------|------------------------------|
| YAGI DIRECTIONAL ANTENNAS | |
| NLOS None Line of Sight | |
| | |
| 626 - 692 MHz | YA62610 |
| | |
| Electrical Data | |
| Gain (dBi) | 10 |
| Front-Back Ratio (dBc) | ≥ 15db |
| VSWR (typical) | 1.5 or less |
| Beamwidth | 68 H 52 V |
| Wind Velocity | 210kmh/130mph |
| Maximum Power | 100W |
| Polarization | Horizontal or Vertical |
| Input Impedance | 50 Ohms |
| | |
| Physical Data | |
| Construction | Aluminum Alloy |
| Connector Interface | N Female |
| Structure | 7 Elements |
| Lightning Protection | DC Ground |
| | |
| Fits Mast Size | 1.5" - 1.97" 40 - 50 mm |
| | |

Photos: Photos for YA Series - YAGI DIRECTIONAL ANTENNA

Photo may not be exact model.

Please note the construction, the materials and the mounting hardware are accurate in photos for all models, only size is different.

Specifications: Specifications subject to change without notice.

Any questions, please contact DMS WIRELESS

<http://www.dmswireless.com>

wireless@dmswireless.com

All products FCA Warehouse, Acworth, GA 30102 USA

One year warranty: Repair or replacement, no freight included.

Contact DMS WIRELESS for RMA.

No returns accepted without RMA.



320 Northpoint Parkway SE
Suite B & C
Acworth, GA 30102 USA
Tel: 770-529-6800
Fax: 770-529-6840
www.dmswireless.com